

PRESET No. 3

L5 112 X/ L Sub 1200 - 130 Hz

Controller Type:

OUTPUT 1		OUTPUT 2		OUTPUT 3		OUTPUT 4		OUTPUT 5		OUTPUT 6	
NAME	L SUB 1200	NAME	L5 112 X	NAME		NAME	L SUB 1200	NAME	L5 112 X	NAME	
Routing	Inp A	Routing	Inp A	Routing		Routing	Inp B	Routing	Inp B	Routing	
Output Gain [dB]	0	Output Gain [dB]	-11,8	Output Gain [dB]		Output Gain [dB]	0	Output Gain [dB]	-11,8	Output Gain [dB]	
Polarity	Norm	Polarity	Norm	Polarity		Polarity	Norm	Polarity	Norm	Polarity	
Delay [ms]	0	Delay [ms]	0	Delay [ms]		Delay [ms]	0	Delay [ms]	0	Delay [ms]	
HPF		HPF		HPF		HPF		HPF		HPF	
Frequency [Hz]	42	Frequency [Hz]	130	Frequency [Hz]		Frequency [Hz]	42	Frequency [Hz]	130	Frequency [Hz]	
Shape	But24	Shape	But24	Shape		Shape	But24	Shape	But24	Shape	
LPF		LPF		LPF		LPF		LPF		LPF	
Frequency [kHz]	130	Frequency [kHz]		Frequency [kHz]		Frequency [kHz]	130	Frequency [kHz]		Frequency [kHz]	
Shape	But24	Shape		Shape		Shape	But24	Shape		Shape	
Low Shelf EQ		Low Shelf EQ		Low Shelf EQ		Low Shelf EQ		Low Shelf EQ		Low Shelf EQ	
Frequency		Frequency		Frequency		Frequency		Frequency		Frequency	
Slope		Slope		Slope		Slope		Slope		Slope	
Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]	
EQ 1		EQ 1		EQ 1		EQ 1		EQ 1		EQ 1	
Frequency	57	Frequency	8,5k	Frequency		Frequency	57	Frequency	8,5k	Frequency	
Width	3,48	Width	6,77	Width		Width	3,48	Width	6,77	Width	
Gain [dB]	0,6	Gain [dB]	-1	Gain [dB]		Gain [dB]	0,6	Gain [dB]	-1	Gain [dB]	
EQ 2		EQ 2		EQ 2		EQ 2		EQ 2		EQ 2	
Frequency	130	Frequency	1,22k	Frequency		Frequency	130	Frequency	1,22k	Frequency	
Width	3,75	Width	3,75	Width		Width	3,75	Width	3,75	Width	
Gain [dB]	-2	Gain [dB]	-1	Gain [dB]		Gain [dB]	-2	Gain [dB]	-1	Gain [dB]	
EQ 3		EQ 3		EQ 3		EQ 3		EQ 3		EQ 3	
Frequency		Frequency	190	Frequency		Frequency		Frequency	190	Frequency	
Width		Width	3,48	Width		Width		Width	3,48	Width	
Gain [dB]		Gain [dB]	-1	Gain [dB]		Gain [dB]		Gain [dB]	-1	Gain [dB]	
EQ 4		EQ 4		EQ 4		EQ 4		EQ 4		EQ 4	
Frequency		Frequency		Frequency		Frequency		Frequency		Frequency	
Width		Width		Width		Width		Width		Width	
Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]	
EQ 5		EQ 5		EQ 5		EQ 5		EQ 5		EQ 5	
Frequency		Frequency		Frequency		Frequency		Frequency		Frequency	
Width		Width		Width		Width		Width		Width	
Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]	
EQ 6		EQ 6		EQ 6		EQ 6		EQ 6		EQ 6	
Frequency		Frequency		Frequency		Frequency		Frequency		Frequency	
Width		Width		Width		Width		Width		Width	
Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]	
High Shelf EQ		High Shelf EQ		High Shelf EQ		High Shelf EQ		High Shelf EQ		High Shelf EQ	
Frequency		Frequency	12k	Frequency		Frequency		Frequency	12k	Frequency	
Slope		Slope	12	Slope		Slope		Slope	12	Slope	
Gain [dB]		Gain [dB]	3,4	Gain [dB]		Gain [dB]		Gain [dB]	3,4	Gain [dB]	
Lim Thresh [dB]	14	Lim Thresh [dB]	11,3	Lim Thresh [dB]		Lim Thresh [dB]	14	Lim Thresh [dB]	11,3	Lim Thresh [dB]	

Legend/ HPF: High Pass Filter; LPF: Low Pass Filter; Lr: Linkwitz Riley, But: Butterworth, Bes: Bessel, Har4th: Hardman 4th order, Har8th: Hardman 8th order