

PRESET No. X		NAME CN115 BI VX				Controller Typ					
OUTPUT 1		OUTPUT 2		OUTPUT 3		OUTPUT 4		OUTPUT 5		OUTPUT 6	
<b>NAME</b>	Low L	<b>NAME</b>	High L	<b>NAME</b>		<b>NAME</b>	Low R	<b>NAME</b>	High R	<b>NAME</b>	
<b>Routing</b>	Inp A	<b>Routing</b>	Inp A	<b>Routing</b>		<b>Routing</b>	Inp B	<b>Routing</b>	Inp B	<b>Routing</b>	
<b>Output Gain [dB]</b>	-8,0	<b>Output Gain [dB]</b>	-9,2	<b>Output Gain [dB]</b>		<b>Output Gain [dB]</b>	-8,0	<b>Output Gain [dB]</b>	-9,2	<b>Output Gain [dB]</b>	
<b>Polarity</b>	Norm	<b>Polarity</b>	Rev	<b>Polarity</b>		<b>Polarity</b>	Norm	<b>Polarity</b>	Rev	<b>Polarity</b>	
<b>Delay [ms]</b>	0	<b>Delay [ms]</b>	0	<b>Delay [ms]</b>		<b>Delay [ms]</b>	0	<b>Delay [ms]</b>	0	<b>Delay [ms]</b>	
<b>HPF</b>		<b>HPF</b>		<b>HPF</b>		<b>HPF</b>		<b>HPF</b>		<b>HPF</b>	
Frequency [Hz]	47,1	Frequency [Hz]	857	Frequency [kHz]		Frequency [Hz]	47,1	Frequency [Hz]	857	Frequency [kHz]	
Shape	Har4th	Shape	Har4th	Shape		Shape	Har4th	Shape	Har4th	Shape	
<b>LPF</b>		<b>LPF</b>		<b>LPF</b>		<b>LPF</b>		<b>LPF</b>		<b>LPF</b>	
Frequency [Hz]	857	Frequency [kHz]	25,4	Frequency [kHz]		Frequency [Hz]	857	Frequency [kHz]	25,4	Frequency [kHz]	
Shape	But24	Shape	But24	Shape		Shape	But24	Shape	But24	Shape	
<b>Low Shelf EQ</b>		<b>Low Shelf EQ</b>		<b>Low Shelf EQ</b>		<b>Low Shelf EQ</b>		<b>Low Shelf EQ</b>		<b>Low Shelf EQ</b>	
Frequency	100Hz	Frequency		Frequency		Frequency	100Hz	Frequency		Frequency	
Slope	12dB	Slope		Slope		Slope	12dB	Slope		Slope	
Gain [dB]	2,6	Gain [dB]		Gain [dB]		Gain [dB]	2,6	Gain [dB]		Gain [dB]	
<b>EQ 1</b>		<b>EQ 1</b>		<b>EQ 1</b>		<b>EQ 1</b>		<b>EQ 1</b>		<b>EQ 1</b>	
Frequency	855Hz	Frequency	855Hz	Frequency		Frequency	855Hz	Frequency	855Hz	Frequency	
Width	1,9Q	Width	1,9Q	Width		Width	1,9Q	Width	1,9Q	Width	
Gain [dB]	-1,6	Gain [dB]	-1,6	Gain [dB]		Gain [dB]	-1,6	Gain [dB]	-1,6	Gain [dB]	
<b>EQ 2</b>		<b>EQ 2</b>		<b>EQ 2</b>		<b>EQ 2</b>		<b>EQ 2</b>		<b>EQ 2</b>	
Frequency	151Hz	Frequency		Frequency		Frequency	151Hz	Frequency		Frequency	
Width	4,0Q	Width		Width		Width	4,0Q	Width		Width	
Gain [dB]	-3,0	Gain [dB]		Gain [dB]		Gain [dB]	-3,0	Gain [dB]		Gain [dB]	
<b>EQ 3</b>		<b>EQ 3</b>		<b>EQ 3</b>		<b>EQ 3</b>		<b>EQ 3</b>		<b>EQ 3</b>	
Frequency	421Hz	Frequency	421Hz	Frequency		Frequency	421Hz	Frequency	421Hz	Frequency	
Width	2,4Q	Width	2,4Q	Width		Width	2,4Q	Width	2,4Q	Width	
Gain [dB]	-2,6	Gain [dB]	-2,6	Gain [dB]		Gain [dB]	-2,6	Gain [dB]	-2,6	Gain [dB]	
<b>EQ 4</b>		<b>EQ 4</b>		<b>EQ 4</b>		<b>EQ 4</b>		<b>EQ 4</b>		<b>EQ 4</b>	
Frequency	1,33k	Frequency	1,33k	Frequency		Frequency	1,33k	Frequency	1,33k	Frequency	
Width	9,1Q	Width	9,1Q	Width		Width	9,1Q	Width	9,1Q	Width	
Gain [dB]	-1,8	Gain [dB]	-1,8	Gain [dB]		Gain [dB]	-1,8	Gain [dB]	-1,8	Gain [dB]	
<b>EQ 5</b>		<b>EQ 5</b>		<b>EQ 5</b>		<b>EQ 5</b>		<b>EQ 5</b>		<b>EQ 5</b>	
Frequency		Frequency	5,86k	Frequency		Frequency		Frequency	5,86k	Frequency	
Width		Width	3,0Q	Width		Width		Width	3,0Q	Width	
Gain [dB]		Gain [dB]	-2,2	Gain [dB]		Gain [dB]		Gain [dB]	-2,2	Gain [dB]	
<b>EQ 6</b>		<b>EQ 6</b>		<b>EQ 6</b>		<b>EQ 6</b>		<b>EQ 6</b>		<b>EQ 6</b>	
Frequency		Frequency		Frequency		Frequency		Frequency		Frequency	
Width		Width		Width		Width		Width		Width	
Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]		Gain [dB]	
<b>High Shelf EQ</b>		<b>High Shelf EQ</b>		<b>High Shelf EQ</b>		<b>High Shelf EQ</b>		<b>High Shelf EQ</b>		<b>High Shelf EQ</b>	
Frequency		Frequency	802	Frequency		Frequency		Frequency	802	Frequency	
Slope		Slope	12dB	Slope		Slope		Slope	12dB	Slope	
Gain [dB]		Gain [dB]	-0,4	Gain [dB]		Gain [dB]		Gain [dB]	-0,4	Gain [dB]	
<b>Lim Thresh [dB]</b>	2,0	<b>Lim Thresh [dB]</b>	-5,0	<b>Lim Thresh [dB]</b>		<b>Lim Thresh [dB]</b>	2,0	<b>Lim Thresh [dB]</b>	-5,0	<b>Lim Thresh [dB]</b>	